

VAS Services	Default mode upon successful subscription	To Activate (Turn on)	To Verify	To Deactivate (Turn off)	How to Use
<b>Call Divert</b> <i>-Unconditional (All calls are diverted)</i>  <i>-Busy (Phone is engaged)</i>  <i>- User Unreachable (Phone and/or ONT is switched off)</i>  <i>-No Reply (Phone is unanswered)</i>	Inactive	Press *21* <Number> #	Press *#21#	Press #21#	NA
	Inactive	Press *67* <Number> #	Press *#67#	Press #67#	
	Inactive	Press *47* <Number> #	Press *#47#	Press #47#	
	Inactive	Press *61* <Number> #	Press *#61#	Press #61#	Call timeout default duration is 20 seconds  User can change the duration by: Press *61*<Number> *duration #  where <b>duration</b> is in seconds, with a value of 1-59 seconds  To verify: Press *#61#
<b>Caller Number Display</b>	Active	NA	NA	NA	NA

<b>Caller Number Non-display</b>	Active	Press *81#	Press *#81#	Press #81#	NA
<b>Call Waiting</b>	Active	Press *43#	Press *#43#	Press #43#	In a conversation between Party A & B:  1) Party C calls B. C will hear a ringback tone, B hears call waiting tone. 2) B press 'hook flash' + 2. A will be put on hold. B & C will be connected. 3) B press 'hook flash' + 2 again. C will be put on hold. A & B resumes their conversation. 4) B press 'hook flash' + 1. A will disconnect; B & C continue their conversation.
<b>Call Barring (Outgoing)</b>	Inactive	Press *34*0000*0#	Press *#34#	Press #34*0000#	NA
<b>Three-Party Conference Call</b>	Active	To add a 3 <sup>rd</sup> caller Party C to conversation between Party A & B, 1. Party A press 'hook flash' to put B on hold 2. Dial Party C's number 3. Party A press 'hook flash' + 3 to connect all three parties.			

Note: "<Number>" refers to the number to be diverted to e.g. 9XXX-XXXX or 8XXX-XXXX.  
"Hook Flash" can also refer to "R" button on the phone.